

## MCMR-2000

# BUILT-IN RECEIVER

1 2 3

ADVANCED

SYSTEM  
NEXA



Built-in receiver for control On / Off. Relay with zero-crossing circuit for optimal service life. The receiver is compatible with all self-learning System Nexa remote controls, Nexa Smart Hub and Nexa Bridge X.

- Control On / Off, for example lighting, electric radiators and smaller motors
- 32 memory slots
- Smart Mode \* compatible
- Compatible with Nexa Bridge X and Nexa smart hub

\* SMART MODE FUNCTION. With devices that support "Smart Mode", you can save up to 3 different favorite scenarios that are easily activated with a Nexa "Smart Mode" transmitter.

Power source	220–240 VAC–50Hz
Max.load	2000 W resistive load
Protocol	System Nexa (433,92 MHz)
Range	Up to 30 m
Memory slots	32
Power consumption	< 1 W standby
IP class	For indoor use
Size, Ø x H	48 x 48 x 25 mm
E-nummer (SE)	17 113 79
EL-nummer (NO)	45 145 27
Art nr   EAN	14227   7330545142273