

MLR-1923

DOORBELL, PLUG-IN

1

2

3

EASY START

SYSTEM
NEXA



Plug-in doorbell with blue LED indicator. In addition to functioning as a standard doorbell with an associated push button, it can also receive signals from a motion detector and magnetic sensor or remote control if desired. There are 6 selectable signals so different transmitters can give different ringtones. The audio level can be set in 4 different levels; High - Medium - Low - Mute.

- Plug-in
- 32 memory slots
- Easy installation
- 6 selectable ringtones
- 4 sound levels
- Range up to 150 meters

Power source	220-240 V~50Hz
Protocol	System Nexa (433,92 MHz)
Range	Up to 150 m
Power consumption	<1 W
IP class	Indoor use
Size, Ø x H	59 x 100 x 37 mm
E-nummer (SE)	53 320 82
EL-nummer (NO)	45 145 66
Art nr EAN	18352 7330545183528

